

Analysis of diffraction by three semi-infinite planes using the Wiener-Hopf method

Original

Analysis of diffraction by three semi-infinite planes using the Wiener-Hopf method / Daniele, Vito; Lombardi, Guido. - ELETTRONICO. - 1:(2008), pp. 1-4. ((Intervento presentato al convegno XXIX General Assembly URSI tenutosi a Chicago, IL (USA) nel August 7-16, 2008.

Availability:

This version is available at: 11583/1946591 since:

Publisher:

URSI

Published

DOI:

Terms of use:

openAccess

This article is made available under terms and conditions as specified in the corresponding bibliographic description in the repository

Publisher copyright

(Article begins on next page)

Analysis of Diffraction by three semi-infinite planes using Wiener-Hopf method

Vito Daniele¹, Guido Lombardi²

¹Dipartimento di Elettronica, Politecnico di Torino, C.so Duca degli Abruzzi 24, 10129 Torino, Italy,
tel.: +390115644068, fax:+39011 564 4099, email: danielle@polito.it

² Dipartimento di Elettronica, Politecnico di Torino, C.so Duca degli Abruzzi 24, 10129 Torino, Italy,
tel.: +390115644012, fax:+39011 564 4099, email: guido.lombardi@polito.it

Abstract

The diffraction of an incident plane wave on three equally spaced half-planes is formulated in terms of Wiener-Hopf (W-H) equations using an equivalent circuit model. The order of matrix factorization is reduced due to the symmetry of the problem. A new solution of this classic Wiener-Hopf problem is proposed and the formulation of the problem is presented for the general case of skew incident plane wave.

1. Formulation

The well-known in literature diffraction problem of three equally spaced semi-infinite PEC planes [1] is formulated in terms of Wiener-Hopf (W-H) equations. We consider the general case of an arbitrary plane wave incident (1) on the structure:

$$\begin{cases} E_z^i = E_o e^{j\tau_o \rho \cos(\varphi - \varphi_o)} e^{-j\alpha_o z} \\ H_z^i = H_o e^{j\tau_o \rho \cos(\varphi - \varphi_o)} e^{-j\alpha_o z} \end{cases} \quad (1)$$

where k is the free-space wave number, $\tau_o = k \sin \beta$, $\alpha_o = k \cos \beta$, and β and φ_o are respectively the zenithal and azimuthal angles of the incident wave. Figure 1 illustrates the geometry of the problem for an E-polarized normal incident plane wave ($\beta = \pi / 2$).




Figure 1: Diffraction on three equally spaced semi-infinite PEC planes: E-polarization. The figure reports the Wiener-Hopf unknowns.

In order to formulate the problem in the spectral domain we apply the Fourier transform to the transverse components of the electromagnetic fields (2):

$$\begin{aligned} \mathbf{V}(\eta, y) &= e^{j\alpha_o z} \int_{-\infty}^{\infty} \hat{\mathbf{y}} \times \mathbf{E}_t(x, y, z) e^{j\eta x} dx \\ \mathbf{I}(\eta, y) &= e^{j\alpha_o z} \int_{-\infty}^{\infty} \mathbf{H}_t(x, y, z) e^{j\eta x} dx \end{aligned} \quad (2)$$

We define an equivalent circuit problem, see Figure 2, where the characteristic admittance of the free space is a matrix [2]:

$$\mathbf{Y}_c = \frac{Y_o}{k\sqrt{\tau_o^2 - \eta^2}} \begin{vmatrix} \tau_o^2 & -\eta \alpha_o \\ -\eta \alpha_o & k^2 - \eta^2 \end{vmatrix} \quad (3)$$




Figure 2: Equivalent Circuit model of the problem under study.

The equivalent circuit models the propagation inside the region defined by the half-planes (region 1, 2 and 3) using a Π model of matrix admittance:

$$\mathbf{Y}_1 = \mathbf{Y}_2 = j\mathbf{Y}_c \tan \frac{\tau d}{2}, \quad \mathbf{Y}_3 = -j\mathbf{Y}_c \frac{1}{\sin \tau d} \quad (4)$$

where $\tau = \sqrt{\tau_o^2 - \eta^2}$.

The circuit nodal analysis provide the three following equations

$$\begin{aligned} \text{node 1} &\Rightarrow (\mathbf{Y}_c + \mathbf{Y}_1 + \mathbf{Y}_3) \mathbf{V}_{1+} - \mathbf{Y}_3 \mathbf{V}_{2+} = \mathbf{A}_{1-} \\ \text{node 3} &\Rightarrow (\mathbf{Y}_c + \mathbf{Y}_1 + \mathbf{Y}_3) \mathbf{V}_{3+} - \mathbf{Y}_3 \mathbf{V}_{2+} = \mathbf{A}_{3-} \\ \text{node 2} &\Rightarrow 2(\mathbf{Y}_1 + \mathbf{Y}_3) \mathbf{V}_{2+} - \mathbf{Y}_3 \mathbf{V}_{1+} - \mathbf{Y}_3 \mathbf{V}_{3+} = \mathbf{A}_{2-} \end{aligned} \quad (5)$$

where \mathbf{V}_{1+} , \mathbf{V}_{2+} and \mathbf{V}_{3+} and $\hat{\mathbf{y}} \times \mathbf{A}_{1-}$, $\hat{\mathbf{y}} \times \mathbf{A}_{2-}$ and $\hat{\mathbf{y}} \times \mathbf{A}_{3-}$ are respectively the Fourier transforms of the transverse electric field on the three apertures $y = 0, -d, -2d$ and the total currents induced on the three half-planes. The previous equations constitute a W-H system of third order where the unknowns and the admittance are respectively vector and matrix of size 2, therefore the W-H problem is a scalar matrix problem of size 6.

The symmetry of the geometry allows to reduce the order of the vector W-H problem. In fact by summing the first two equations we get the following system of equations:

$$\begin{cases} (Y_c + Y_I + Y_3)(V_{I+} + V_{3+}) - 2Y_3 V_{2+} = A_{I-} + A_{3-} \\ -Y_3(V_{I+} + V_{3+}) + 2(Y_I + Y_3)V_{2+} = A_{2-} \end{cases} \quad (6)$$

Equation (6) is a homogeneous vector W-H problem of order 2 ($\mathbf{G} \cdot \mathbf{V}_+ = \mathbf{A}_-$), where the plus unknowns are $(V_{I+} + V_{3+})$ and $2V_{2+}$, the minus unknowns are $(A_{I-} + A_{3-})$ and A_{2-} and the kernel takes the following form:

$$\mathbf{G} = \begin{vmatrix} (Y_c + Y_I + Y_3) & -Y_3 \\ -Y_3 & (Y_I + Y_3) \end{vmatrix} = Y_c \otimes \mathbf{H} \quad (7)$$

where the operator \otimes is the Kronecker matrix product and where

$$\mathbf{H} = \begin{vmatrix} 1 - j \cot(\tau d) & j \csc(\tau d) \\ j \csc(\tau d) & -j \cot(\tau d) \end{vmatrix} = \frac{2}{1 - e^{-2j\tau d}} \begin{vmatrix} 1 & -e^{-j\tau d} \\ -e^{-j\tau d} & \left(\frac{1 + e^{-j\tau d}}{2} \right) \end{vmatrix} \quad (8)$$

2. Solution

In order to obtain the solution of the Wiener-Hopf problem we need to factorize (7).

By applying the mixed-product property of the Kronecker product (9) to the plus and minus factorized matrices of \mathbf{Y}_c and \mathbf{H} we obtain the factorization of \mathbf{G} , see (10).

$$A \cdot C \otimes B \cdot D = A \otimes B \cdot C \otimes D \quad (9)$$

$$\mathbf{G} = \mathbf{G}_- \cdot \mathbf{G}_+ = \mathbf{Y}_{c-} \cdot \mathbf{Y}_{c+} \otimes \mathbf{H}_- \cdot \mathbf{H}_+ = \mathbf{Y}_{c-} \otimes \mathbf{H}_- \cdot \mathbf{Y}_{c+} \otimes \mathbf{H}_+ \quad (10)$$

From the homogenous Wiener-Hopf equation (6) we obtain the normal form ($G(\alpha)F_+(\alpha) = F_-(\alpha) + F_{o+}(\alpha)$) by extracting the source term related to the incident plane wave:

$$\mathbf{G} \cdot \mathbf{V}_+ = \mathbf{A}_-^d + \frac{\mathbf{R}_o}{\eta - \eta_o} \quad (11)$$

\mathbf{R}_o is the source obtained as GO component from the incident field.

We remind the spectral quantities are functions of the spectral variable η . The solution takes the following form:

$$\begin{cases} \mathbf{V}_+(\eta) = \mathbf{G}_+^{-1}(\eta) \cdot \mathbf{G}_+^{-1}(\eta_o) \cdot \frac{\mathbf{R}_o}{\eta - \eta_o} \\ \mathbf{A}_-(\eta) = \mathbf{G}_-(\eta) \cdot \mathbf{V}_+(\eta) = \mathbf{G}_-(\eta) \cdot \mathbf{G}_+^{-1}(\eta_o) \cdot \frac{\mathbf{R}_o}{\eta - \eta_o} \end{cases} \quad (11)$$

We note that the matrix \mathbf{Y}_c can be factorized in closed form. However no exact factorization has been obtained for matrices \mathbf{G} and \mathbf{H} up to now, therefore we can apply the approximate procedure presented in [3, 4] based on integral equations. Numerical results will be presented at the Conference.

3. Acknowledgments

This work was supported by NATO in the framework of the Science for Peace Programme under the grant CBP.MD.SFPP 982376.

4. References

1. D.S. Jones, "Diffraction by three semi-infinite planes," *Proc. Royal Soc. London*, **A404**, 1986, pp. 299–321.
2. V. Daniele, "Electromagnetic propagation in plane stratified regions," Internal Report ELT-2006, Politecnico di Torino, 2006, available at <http://www.eln.polito.it/staff/daniele>.
3. V. Daniele and G. Lombardi, "Wiener-Hopf solution for impenetrable wedges at skew incidence," *IEEE Trans. Antennas Propag.*, **AP-54**, 2006, pp. 2472-2485, doi:10.1109/TAP.2006.880723.
4. V. Daniele, and G. Lombardi, "Fredholm factorization of Wiener-Hopf scalar and matrix kernels," *Radio Science*, **42**, 2007, RS6S01, doi:10.1029/2007RS003673.